

# SDL

## Lighting

### RGB CONTROLLER MODULE

#### SDL-3600RC RGB LED Controller



The SDL-3600RC LED RGB Controller can be used to drive RGB FlexLED SMT and PowerStrip V15/30 in conjunction with a suitable 12/24v dc power supply. The SDL-3600RC LED Controller will drive up to 30m of RGB FlexLED SMT. 17 modes of colour skipping, colour gradual changes and with the option of speed and brightness control.

#### Specifications

Voltage	12/24 V dc
Connections	Screw Terminal
Ambient Temperature	-20 to +50 Degrees Centigrade
Output	3 x 6 Amp
Control Interface	7 Button unit / RF Remote
Changing Mode	17 modes
Colour Depth	256 levels
Mounting	Surface
Dimensions	211mm x 40mm x 30mm